

DDNS setup guide

Step 1: Please use web browser on your PC or notebook and type in URL <http://kguard.org> to connect to KGuard DDNS website to register.



Welcome to kguard.org

Create a user account or choose existing users below to begin.

DDNS account creation.

NEW USER REGISTRATION	
EMAIL ADDRESS	<input type="text"/>
PASS WORD	<input type="password"/>
PASS WORD CONFIRM	<input type="password"/>
FIRST NAME	<input type="text"/>
LAST NAME	<input type="text"/>
SECURITY QUESTION.	<input type="text" value="My first phone number. ▼"/>
ANSWER	<input type="text"/>
CONFIRM YOU'RE HUMAN	<div>$8+6=$ New Captcha <input type="text"/> Solve the problem above.</div>
<input type="button" value="Submit"/> <input type="button" value="Reset"/>	

Already have an account? [Click here to logon.](#)

Step 2: Please enter Email address, password, first name, last name, security question, answer and verification code. Please click “**Submit**” button when you complete °



[Ligon](#)

[Registration](#)

Welcome to kguard.org

Create a user account or choose existing users below to begin.

DDNS account creation.

NEW USER REGISTRATION	
EMAIL ADDRESS	<input type="text" value="support@kguard.com.tw"/>
PASS WORD	<input type="password" value=""/> 
PASS WORD CONFIRM	<input type="password" value=""/>
FIRST NAME	<input type="text" value="kguard"/>
LAST NAME	<input type="text" value="support"/>
SECURITY QUESTION.	<input type="text" value="My first phone number. ▼"/>
ANSWER	<input type="text" value="xxxxxxxx"/>
CONFIRM YOU'RE HUMAN	<div><div>7+8=</div><div>New Captcha</div><div><input type="text" value="15"/></div><div>Solve the problem above.</div></div>
<input type="button" value="Submit"/> <input type="button" value="Reset"/>	


Already have an account? [Click here to logon.](#)

Step 3: Please enter domain name you want to register. For example: mr400 and click “Request Domain” button.



The screenshot shows the 'Domain Name Creation' page of the KGUARD SECURITY interface. On the left, there are three buttons: 'User Settings', 'Domains', and 'Logout'. The main heading is 'Domain Name Creation' with a subtext 'Enter a new domain name below.' Below this, a text input field contains 'mr400', followed by a dropdown menu showing '.kguard.org'. A red box highlights the input field and the dropdown. To the right of the dropdown is a 'Request Domain' button. Above the input field, a note states: 'Domain name must start with (a-z, 0-9). Cannot end or start, but may contain a hyphen and is not case-sensitive.' At the bottom, a footer reads 'All Rights Reserved © 2010 kguard.org'.

Step 4: After register complete, you can see your domain on web page.




The screenshot shows the 'My Domains' page of the KGUARD SECURITY interface. On the left, there are three buttons: 'User Settings', 'Domains', and 'Logout'. The main heading is 'My Domains' with a subtext 'Your domain names are listed below. Choose create new domain to add additional domain names.' Below this, there is a search bar with the text 'Search by Domain.' and a 'Search' button. A red box highlights a table containing domain information. Above the table, a link says 'Click a name to edit your domain settings.' The table has three columns: 'NAME', 'STATUS', and 'DOMAIN'. The first row shows 'MR400' in the NAME column, a green checkmark in the STATUS column, and 'mr400.kguard.org' in the DOMAIN column. Below the table, a footer reads 'Last Update: 2014/10/2 下午 01:43:33 IP Address: 124.219.78.137'.

NAME	STATUS	DOMAIN
MR400	✓	mr400.kguard.org

Step 5: Login Mars Home device and click“  (Main Menu)” enter setup menu.



Step 6: Please click “Network”



Step 7: Select “**DDNS**”→set DDNS to “**Enable**” and enter the info below:

Server: “KGUARD.ORG”


Domain: enter domain name you register. For example: kg.kguard.org

User: Enter the email you register at our DDNS website in Step 2, for example:

support@kguard.com.tw

Password: Enter the password you register at our DDNS website in Step 2.


Please click “**Apply**” when you are complete.



Display will pop-up message “**Save parameters complete**” , please click “**OK**” .




Step 8: Please click “**Test**” button to check connection status, please click “**OK**”




After test complete, display will show “**Test Succeeded**” message, please click “**OK**”

※If display does not show DDNS test succeeded message, please check your network setting is correct. For example: network connection is normal, DDNS hostname is correct, email is correct and password is correct.



Step 9: Open web browser on your PC or notebook and enter your domain name, for example: mr400.kguard.org, you can see DVR's login page. Enter the user, password and click “**Login**” button to see DVR camera video.





(Setup complete)